Electro-optic Polymer / Titanium Dioxide Hybrid Modulators

Feng Qiu*, and Shiyoshi Yokoyama

Institute for Materials Chemistry and Engineering, Kyushu University E-mail: drfqiu@cm.kyushu-u.ac.jp

1. Introduction

Organic EO polymer can provide a high EO coefficient $(r_{33}) > 100 \text{ pm/V}$, ultrafast EO response time, very low dispersion of up to 250 GHz, and facile compatibility with other materials. Because of these outstanding properties it is highly desirable to utilize EO polymer in telecommunications to enlarge the bandwidth and to benefit from state-of-the-art CMOS fabrication capabilities. Here, we present our novel modulators based on the EO polymer / titanium dioxide (TiO₂) hybrid structure [1, 2].

2. Method and Results

2.1 Micro-ring resonator modulator

The advantages of such modulators are their compact footprint, low driving voltages, and the ability to drive them as lumped RF elements to eliminating the need for traveling-wave design. However, conventional EO polymer waveguide modulators have a bending radius of around one millimeter, thereby limiting the miniaturization of the modulators. Additionally, the typical inter-electrode distances in such waveguides are ~10 μ m, but the thickness of the EO core is ~3 μ m. This means that there is a large voltage in the modulator dropping across the thick cladding layers, resulting in a small resonance shift control and a high peak to peak voltage V_{p-p}.



Fig. 1 (a) Designed cross-section of the TiO_2 core / EO polymer ring resonator waveguide; (b) simulated TM_{00} mode intensity distribution; (c) top view SEM image of the TiO_2 ring structure (left: view of cross-section, right: view of bus-ring gap).

The ring resonator modulator fabricated in this study was constructed using a thin TiO_2 ridge waveguide and EO polymer cladding layer, but without a traditional transparent cladding. The 250 nm thick TiO_2 has the benefits of a

shortened electrode distance, a substantially improved poling efficiency, and a minimized ring radius in the 100 μ m scale. As a result, our modulator shows the highest resonance a tunability of 0.02 nm/V and an in-device r₃₃ of 105 pm/V. A modulation depth of 3dB was observed at the frequency response function at 20 kHz using a 2 V_{p-p} clock signal.

2.2 Nano-line modulator

Integrated EO polymer devices on silicon photonics have a number of potential applications. These include telecommunications switches, signal amplifiers, and filter circuits. Another application of these devices is as optical interconnects between functional modules on a microchip or between microchips on a printed circuit board as a potential replacement for metal interconnect technology, which is nearing its limit with copper interconnects

An electro-optic (EO) modulator composed of an EO polymer / TiO₂ hybrid waveguide has been designed and fabricated. By using a TiO₂ strip line ($0.3 \times 0.3 \ \mu m^2$ cross-section) as the core, the confinement factor in the EO polymer is optimized for the highest EO activity. The coplanar electrode spacing is examined to enable effective poling and a small propagation loss. The measured in-device EO coefficient is 100 pm/V at 1550 nm wavelength, and a V π is 3.2V for the 12 mm-electrode length. The results also predict a possible V π of ~1V in a push-pull Mach-Zehnder interferometer structure. The modulator exhibited an excellent temporal stability for the EO activity at 85 °C for 500 hours due to the high glass transition temperature of the EO polymer and the temperature-insensitive TiO₂ strip line.



Fig. 2 SEM images of the top-view and oomed in TiO_2 channel (after coating EO polymer) of the modulator

References

- F. Qiu, A. M. Spring, F. Yu, and S. Yokoyama, Appl. Phys. Lett. 102(5), 051106 (2013)
- [2] F. Qiu, A. M. Spring, A. Otomo, and S. Yokoyama, Laser Photonics Rev. 7 (6), 84 (2013)